

# Pulse Oximeter

## Fingertip Pulse Oximeter SONOSAT-F01LT

Monitor Parameter : SpO2 , HR



Recharge lithium battery



Bluetooth 4.0



Fashion Appearance



Lightweight



App support



### Feature

- Fresh and elegant pattern, smart and light;
- 0.95" LCD screen, high resolution;
- Building lithium battery and USB charging;
- Bluetooth 4.0 build-in and APP support;
- Good anti-wrestling character,
- Still working properly even after dropping from the high place of 1.2m;
- Thin and light body with 24 mm thick and 36 g weight;
- Suitable for: Pregnant, old people, sport man and person with chronic obstructive pulmonary disease;

Support for review/monitoring  
by application in mobile

### Technical Specifications



|                          |   |
|--------------------------|---|
| Model                    | SONOSAT-F01LT                               |
| Display Type             | LCD: 0.96"                                  |
| Maximum Weight           | 50(g) (Including battery)                   |
| Parameter                | PR,SPO2                                     |
| Spo2 measurement Rang    | 0% ~ 100%                                   |
| Spo2 Resolution          | 1%  |
| Spo2 Accuracy            | 70% ~ 100%, ±2%, Less than 70%, unspecified |
| PR(BMP) Measurement Rang | 18bpm ~ 250bpm                              |
| PR Resolution            | 1%  |
| PR Accuracy:             | 25bpm ~ 250bpm, ±3bpm                       |
| Battery                  | Lithium, Run Time:16h, Charge Time: 2h      |
| Battery Service Life     | 500 times of charge-discharge               |

Jiangsu Konsung Bio-Medical Science and Technology Co.,Ltd

Headquater: NO.8, Shengchang West Rd, Economy Development Zone,

Danyang, Jiangsu, China

Tel: 86-511-86375968

Fax: 86-511-86371668

Mail: Info@konsung.com

Shenzhen Add : 14th floor, Building 1, 2nd New Magic Industry Park , No.1 Liuxian road ,  
67th Bao'an district, Shenzhen